FIRE DETECTION AND SUPPRESSION CONTROL

INNOVEX

Fire alarm and extinguishant release control panels



A-XT / A-CP control panels

Two panels, one platform

INNOVEX control panels support conventional fire detection and clean agent extinguishant release. A common steel enclosure and accessible controls simplify installation, operation and service.

A-XT

Extinguishant release control.
Three configurable initiating circuits.

A-CP

Conventional fire alarm control.
Two, four or eight initiating circuits.

© SAFETY HI-TECH GLOBAL 2026. All rights reserved.

PANEL SPECIFICATIONS

Detection and release control

A-XT

Extinguishant control panel

Initiating circuits
3, configurable for ceiling void, room and floor void detection.

Release settings
Delay: 0–60 seconds in 5-second steps.
Duration: 60–300 seconds in 5-second steps.

Remote status units
Up to 7 units via RS-485, with local countdown indication.

Power and batteries
115 or 230 V AC; 3 A total including battery charge. Two 12 V 7 Ah batteries in series.

Enclosure
368 × 310 × 90 mm; 1.2 mm mild steel; IP30. Red RAL 3002; optional grey BS 00 A 05.

A-CP

Conventional fire alarm panel

Initiating circuits
2, 4 or 8 zones, configurable as Fire, Waterflow or Supervisory.

Notification circuits
Two 2 A NAC circuits, 4 A total, with selectable synchronization protocols.

Power and standby
115 or 230 V AC; 24 V 6.5 A DC output. Up to 72-hour standby with 7 Ah batteries.

Communications
RS-485 bus for annunciators and ancillary relay boards. Optional dual-line DACT with 500-event history.

Enclosure
368 × 310 × 110 mm; 1.2 mm mild steel; IP30. Red or grey finish.

Remote status indication





A-XT remote units display system status and time remaining until discharge. Versions shown with and without a mode-selection key switch.

UL Listed / FM Approved

Safety Hi-Tech Global certification

SAFETY HI-TECH GLOBAL LLC
16192 Coastal Highway
Lewes, Delaware 19958 USA

info@sht-global.com
www.sht-global.com

© SAFETY HI-TECH GLOBAL 2026. All rights reserved.